

Message formats for Threat to Peace or Detention Officer Addresses Transactions

ENTA -- Enter Supplemental Threat to Peace or Detention Officer Addresses

Message Structure:

{ssss}TCC#\$1N01rrrr ccccccccc.ENTA.<ori>

Such That:

ssss	4	Mnemonic of Sending Device
rrrr	4	Mnemonic of Receiving Device
cccccccc	1-10	Control Field; Used for routing within the interface system
.<ori>	9	Agency's FBI assigned Originating Agency Identifier

Followed By (Selection Criteria):

.NAM/<nam>	3-30	Name. The name may include alphabetic, numerics, a comma, hyphen(s), and spaces. The comma must follow the last name. The hyphen cannot be in the first position or directly precede the comma.
.OCA/<oca>	1-20	Originating Case Number. The only valid special characters are the hyphen and the space. Other exceptions are described in the NCIC 2000 Operating Manual.

Followed by at least one of the following:

.ADR/<adr>	1-30	Set - 1	Address
.<adc>	1-20	Set - 1	City
.<ads>	2	Set - 1	State
.<adz>	5 or 9	Set - 1	Zip
.<aty>	1	Set - 1	Address Type. H = home or W = work.
.<sts>	1	Set - 1	Address Status. C = current or F = former.
.<loc>	1-20	Set - 1	Address Location. Free text.
.TNO/<tno>	10	Set - 2	Telephone Number. Ten numeric digits. Example: 5124442000.
.<nty>	1	Set - 2	Telephone number type. H = home; W = work; M = mobile; P = pager.

XNTA -- Cancel Supplemental Threat to Peace or Detention Officer Addresses

Message Structure:

{ssss}TCC#\$1N01rrrr ccccccccc.XNTA.<ori>

Such That:

ssss	4	Mnemonic of Sending Device
rrrr	4	Mnemonic of Receiving Device
cccccccc	1-10	Control Field; Used for routing within the interface system
.<ori>	9	Agency's FBI assigned Originating Agency Identifier

Followed By (Selection Criteria):

.NAM/<nam>	3-30	Name. The name may include alphabetic, numerics, a comma, hyphen(s), and spaces. The comma must follow the last name. The hyphen cannot be in the first position or directly precede the comma.
.OCA/<oca>	1-20	Originating Case Number. The only valid special characters are the hyphen and the space. Other exceptions are described in the NCIC 2000 Operating Manual.

Followed by at least one of the following:

.ADR/<adr>	1-30	Set - 1	Address
.<adc>	1-20	Set - 1	City
.<ads>	2	Set - 1	State
.<adz>	5 or 9	Set - 1	Zip
.<aty>	1	Set - 1	Address Type. H = home or W = work.
.<sts>	1	Set - 1	Address Status. C = current or F = former.
.<loc>	1-20	Set - 1	Address Location. Free text.
.TNO/<tno>	10	Set - 2	Telephone Number. Ten numeric digits. Example: 5124442000.
.<nty>	1	Set - 2	Telephone number type. H = home; W = work; M = mobile; P = pager.